

IN THE CLAIMS

1. (Currently Amended) A method of installation of a receiver to receive broadcast data for use to generate audio and/or video at each receiver ~~which is~~ broadcast continuously to a plurality of locations including the location of the receiver, said method comprising;

measuring the power level of ~~incoming~~ the broadcast data signal ~~s used to generate at least video or audio data~~ at two predetermined spaced points on the signal band by measuring the content of automatic gain control converters relating to said broadcast data signal within the receiver; ~~and~~

providing an amplitude correction filter which can be selectively operated on said broadcast data signal[s] to allow the correction of amplitude variations ~~which~~ with frequency, the selective operation of the filter dependent upon and responsive to the power level measurements obtained; and
wherein

the broadcast data signal used for the measurement of the content is the same as that used to generate the audio and/or video at the receiver locations for display at the receiver location for the purpose of viewing the display.

2. (Previously Presented) A method of installation according to claim 1 wherein during the installation procedure obtaining the power level measurements occurs automatically and is followed by any required correction as part of an automatic installation procedure.

3. (Previously Presented) A method of installation according to claim 1 wherein two measurements are taken, referred to as the high end signal and the low end signal.

4. (Previously Presented) A method of installation according to claim 3 wherein if said high end signal level is greater than said low end signal level, then no linearization via the filter is performed.

5. (Previously Presented) A method of installation according to claim 1 wherein if the difference in power levels between said points is greater than a predetermined level then the power level to said broadcast data receiver is adjusted so that the incoming signal is within a known power range.

6. (Previously Presented) A method of installation according to claim 1 wherein said method utilizes the ability to use relative signal power level rather than absolute signal power level to install the receiver.

7. (Currently Amended) A broadcast data receiver apparatus for receiving broadcast digital data for use to generate audio and/or video at each receiver which is continuously transmitted to a plurality of locations, received by the apparatus and passed to the receiver via a radio frequency input from the data carrying network, said receiver comprising:

a linearization circuit which can be selectively activated to operate with a receiver control system upon comparison of measurements of the power levels at two predetermined points on the broadcast data signal passed to the radio frequency input;

~~said signal used to generate at least video or audio data by the apparatus; and~~

if the comparison reveals a difference which is greater than a predetermined level, the linearization circuit is activated to adjust the receiver settings during an installation procedure for

the broadcast data receiver at a location at which the receiver is to be subsequently used; and wherein[.]

the broadcast data signal used for the measurements is the same as that used to generate the audio and/or video at the receiver locations for display at the receiver location for the purpose of viewing the display

8. (Previously Presented) A broadcast data receiver according to claim 7 wherein said receiver is connected to a data supply network in which the data is carried by a cable network.

9. (Previously Presented) A broadcast data receiver according to claim 8 wherein the linearization circuit is selectively activated automatically by said receiver control system upon specified criteria for activation being met.

10. (Previously Presented) A broadcast data receiver according to claim 8 wherein said linearization circuit is selectively activated by a receiver installer upon the installer receiving an indication, by visual and/or audio indication means, that specified criteria for operation of said linearization circuit have been met

11. (Previously Presented) A broadcast data receiver according to claim 8 wherein said linearization circuit performs cable slope correction internally in said broadcast data receiver and this can be applied to improve the performance of the broadcast data receiver at the location of installation.

12. (Previously Presented) A broadcast data receiver according to claim 11 receiving a high end signal and a low end signal wherein the internal changes performed can include changing the value of inductors, capacitors and/or resistors to obtain one of a number of equalization slopes to bring the difference between the high end signal and low end signal within a specific margin.

13. (Previously Presented) A broadcast data receiver according to claim 12 wherein the linearization circuit is selectively activated when the difference between said high end and said low end signal values is greater than 10 dB.

14. (Currently Amended) A method of installation of a receiver by a user to receive digital data for use to generate audio and/or video at each receiver ~~which is~~ continuously broadcast to a plurality of locations including the location of the receiver, said method comprising:

measuring the power level of incoming frequency signals relating to said digital data at two predetermined spaced points on the signal band; ~~and~~ ;

providing means for the comparison of the measurements and if the comparison shows a value within a predetermined parameter an indication is provided to the user and if the comparison shows a value out with the predetermined parameter a control system in the receiver adjusts the operation of one or a combination of components within the receiver until the value is within the predetermined parameter[.]; and wherein

the signal used for the measurements is that from which the audio and/or video is generated at the receiver locations for display at the receiver location for the purpose of viewing the display.

15. (Previously Presented) A method of installation according to claim 14 wherein said control system adjusts said operation with reference to at least one algorithm in the control system.

16. (Previously Presented) A method of installation according to claim 14 wherein the components which are adjusted are selected from a group consisting of capacitors, inductors, resistors provided as part of a circuit installed in the broadcast data receiver.